HEATMISER CONTROLS

Heatmiser neoAir Wireless Programmable Smart Thermostat

Battery thermostat, no cables to chase.

A wireless smart thermostat on 4 AAA batteries, with no cable back to the wiring centre. Ideal for retrofit UFH and finished rooms: it pairs with the UH8-RF wiring centre or the RF-Switch, and a neoHub adds control from the neoApp.

CODES

HM-NEOAIR-W, -B, -S



01 · KEY FEATURES

Why installers use it

- No thermostat cable: fit it without chasing walls
- **Three modes: thermostat,** timer, or heating and timer together
- App control through the neoApp with a neoHub
- Pairs with the Heatmiser UH8-RF or RF-Switch receivers

IN THE BOX

neoAir thermostat | Fixing screws

02 · SPECIFICATION

Technical data

Power	4 x AAA batteries
Max switching current	3A (at the receiver)
Temperature range	5 to 35°C
Programming	Non-programmable, 5/2, 7 day, 24 hour
Size (L x H x D)	86 × 86 × 26mm
Colours	Glacier White, Sapphire Black, Platinum Silver

03 · DESIGN HELP

Send us your plans

For design help, send your plans to **sales@maxheatufh.com** or plan loops with **MaxHeatUFH ProLoop** at maxheatufh.com.

04 · COLOURS AND CODES

Pick the colour, one code each.

3 options by colour. Order by code.

COLOUR	CODE
Glacier White	HM-NEOAIR-W
Sapphire Black	HM-NEOAIR-B
Platinum Silver	HM-NEOAIR-S

05 · WORKS WITH

Complete the system

- Heatmiser UH8-RF Wireless Wiring Centre
- Heatmiser RF-Switch Two Channel Receiver
- Heatmiser neoHub G3 for app control

06 · FITTING AT A GLANCE

Full steps in the install manual

1. Fit the receiver first: a UH8-RF at the manifold, or an RF-Switch at the boiler or heater (mains work for a qualified electrician).
2. Fit the batteries and mount the neoAir on the wall away from draughts, direct sun and heat sources.
3. Pair the neoAir to its receiver zone, following the Heatmiser pairing steps supplied.
4. Choose the mode: thermostat, timer, or heating and timer (the timed output can run hot water).



07 · AT A GLANCE

Heatmiser neoAir Wireless Programmable Smart Thermostat

POWER

4 x AAA batteries

MAX SWITCHING CURRENT

3A (at the receiver)

SCAN ME

Watch how it works and fits

Point your phone camera at the code to watch the video for this product.

DESIGN HELP, TRADE ACCOUNTS AND ORDERS

sales@maxheatufh.com **07539 499069**

WEB
maxheatufh.com

DELIVERY
Order by 12pm for next working day delivery